

## **FVR-1211U5B**

Forza's Automatic Voltage Regulator --also known as line conditioner-- is the reliable solution that provides the right protection for your equipment.



In addition to its excellent stabilization capability, the FVR automatically corrects transient voltage fluctuations and filters out electrical noise to provide "clean", regulated AC power. Forza's FVR- 1211USB is the perfect choice to enhance performance and safeguard your valuable components.

## Highlights

- Automatic Voltage Regulator (AVR)
- Instantaneously switches to correct output voltage by closely monitoring the input voltage
- Two USB charging ports for smart phones and tablets
- Power protection for all your sensitive electronics and peripherals in a space saving design
- User-friendly LED status indicators
- Phone and data line protection
- Built-in advanced thermofuse protection it disconnects power when temperature is dangerously high
- Overload protection circuit breaker
- Can be mounted on the wall











MPN	FVR-1211USB
General	
Capacity	1200VA/600W
Input	
Voltage	115V
Voltage range	86 -138VCA
Frequency	50/60Hz (autosensing)
Joules	320J
Max spike current	4500A
AC plug style	NEMA 5-15P
Output	
Outlet type	8 (NEMA 5-15R)
Voltage range	104-126VCA
Frequency	50/60Hz
Delay timer	2 sec - 10 sec - 30 sec
Regulation steps (3)	2 boost / 1 buck
Overload protection	Thermofuse
USB charging port	Two 5V ports (2.4A max)
Data protection	
Network protection	RJ-45
Phone/modem/fax protection	RJ-11
Joules	27J
Voltage regulation	
Voltage regulation	115V
Boost	108VAC
Boost	100VAC
Buck	122VAC
Visual indicators	
LEDs	4
Power on	Green
Boost	Green
Buck	Green
Overheart/cut-off	Red
Environment	
Operating temperature	32-104°F
Storage temperature	5-133°F
Relative humdity	0-95% no condensing
Audible noise	<40dB at one meter
Physical appearance	
Switch	Illuminated
Housing	Flame retardant plastic
Color	Black
Color length	3.9ft
Dimensions	7.2x6.1x3.1in
Weight	3.3lb
Additional information	
Warranty	2 years









